

**DESCRIPTION**


The **GEFCO Select #EE-962** DMX Controlled Relay System provides a series of 8 each 10A 110V SPDT load control relays under the control of 4 DMX channels for 8 individual ON/OFF commands. The board is DMX addressable using the on-board DMX DIP Switch to set individual DMX address along with DMX termination terminal.

THESE RELAYS ARE NON-DIMMABLE.

The commands can be controlled from any DMX control device or a GEFCO Select #EE965, #EE966 or #EE960 RGB DMX Controller (ORDER SEPARATELY) that will control up to 512 control points per Universe or other DMX sources. This system is open frame and mountable in an optional plastic NEMA 1 enclosure. Final Assembly in the USA

**TYPICAL SPECIFICATIONS:**

- \* **GEFCO Select #EE-962** DMX Controlled Relay System:
  - printed circuit board
  - 8 ea. 10A SPDT relay switch 120VAC
  - 15-24VDC control power
  - 9 position DMX Address switch.
  - on board DMX activity LED light
  - DMX input terminals.
  - DMX termination resistor terminal w/ closing jumper
  - SPDT wire terminals.
  - 4.25" x 3" x 1" open frame
  - mountable in control panels or optional NEMA 6" x 6" x 4" enclosures
  - weight: WITH enclosure 1 lbs.



**IMPORTANT**

*The designers, installers and end users utilizing the electrical equipment described herein assume full responsibility for the compliance with the N.E.C. and it's applicable articles, intents and consequences. Where the manufacturer and/or the supplier of the electrical equipment described herein does not control the application or usage, he assumes no responsibility whatsoever for any consequences arising out of the application, installation and/or usage of this or any other equipment and/or materials.*

**IMPORTANT**

*Dimensions and/or Materials subject to change without notice*